



GVM-PRO-BD45R

DMX Channel Table

Content

Mode 1: CCT&RGB 8-bit PIXEL=33	1
Mode 2: CCT&HSI 8-bit PIXEL=33	1
Mode 3: CCT 8-bit PIXEL=33	1
Mode 4: RGB 8-bit PIXEL=33	1
Mode 5: HSI 8-bit PIXEL=33	2
Mode 6: CCT&RGB 8-bit PIXEL=11	2
Mode 7: CCT&HSI 8-bit PIXEL=11	3
Mode 8: CCT 8-bit PIXEL=11	3
Mode 9: RGB 8-bit PIXEL=11	4
Mode 10: HSI 8-bit PIXEL=11	4
Mode 11: CCT&RGB 8-bit PIXEL=3	4
Mode 12: CCT&HSI 8-bit PIXEL=3	6
Mode 13: CCT 8-bit PIXEL=3	7
Mode 14: RGB 8-bit PIXEL=3	7
Mode 15: HSI 8-bit PIXEL=3	8
Mode 16: CCT&RGB 8-bit PIXEL=1	8
Mode 17: CCT&HSI 8-bit PIXEL=1	10
Mode 18: CCT 8-bit PIXEL=1	10
Mode 19: RGB 8-bit PIXEL=1	11
Mode 20: HSI 8-bit PIXEL=1	12
Mode 21: EFFECT 8-bit	12
Mode 22: PIXEL FX 8-bit	13

CCT&RGB 8-bit PIXEL=33			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->RGB	Crossfade to Color
5	0-255	R(0-255)	Red
6	0-255	G(0-255)	Green
7	0-255	B(0-255)	Blue

CCT&HSI 8-bit PIXEL=33			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->HSI	Crossfade to Color
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	Saturation

CCT 8-bit PIXEL=33			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	

RGB 8-bit PIXEL=33			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-255	R(0-255)	Red
3	0-255	G(0-255)	Green
4	0-255	B(0-255)	Blue

HSI 8-bit PIXEL=33			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-255	HUE(0°-360°)	
3	0-255	SAT(0%-100%)	Saturation

CCT&RGB 8-bit PIXEL=11			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->RGB	
5	0-255	R(0-255)	
6	0-255	G(0-255)	
7	0-255	B(0-255)	
8	0-255	INT(0%-100%)	PIXEL2
9	0-255	CCT(2700K-10000K)	
10	0-255	GM(-50-50)	
11	0-255	CCT<-->RGB	
12	0-255	R(0-255)	
13	0-255	G(0-255)	
14	0-255	B(0-255)	PIXEL3
15	0-255	INT(0%-100%)	
16	0-255	CCT(2700K-10000K)	
17	0-255	GM(-50-50)	
18	0-255	CCT<-->RGB	
19	0-255	R(0-255)	
20	0-255	G(0-255)	
21	0-255	B(0-255)	

CCT&HSI 8-bit PIXEL=11			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->HSI	
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL2
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	
10	0-255	CCT<-->HSI	
11	0-255	HUE(0°-360°)	
12	0-255	SAT(0%-100%)	
13	0-255	INT(0%-100%)	PIXEL3
14	0-255	CCT(2700K-10000K)	
15	0-255	GM(-50-50)	
16	0-255	CCT<-->HSI	
17	0-255	HUE(0°-360°)	
18	0-255	SAT(0%-100%)	

CCT 8-bit PIXEL=11			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	CCT(2700K-10000K)	
6	0-255	GM(-50-50)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	

RGB 8-bit PIXEL=11			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	R(0-255)	
3	0-255	G(0-255)	
4	0-255	B(0-255)	
5	0-255	INT(0%-100%)	PIXEL2
6	0-255	R(0-255)	
7	0-255	G(0-255)	
8	0-255	B(0-255)	
9	0-255	INT(0%-100%)	PIXEL3
10	0-255	R(0-255)	
11	0-255	G(0-255)	
12	0-255	B(0-255)	

HSI 8-bit PIXEL=11			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	HUE(0°-360°)	
3	0-255	SAT(0%-100%)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	HUE(0°-360°)	
9	0-255	SAT(0%-100%)	

CCT&RGB 8-bit PIXEL=3			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->RGB	

5	0-255	R(0-255)	PIXEL2
6	0-255	G(0-255)	
7	0-255	B(0-255)	
8	0-255	INT(0%-100%)	
9	0-255	CCT(2700K-10000K)	
10	0-255	GM(-50-50)	
11	0-255	CCT<-->RGB	
12	0-255	R(0-255)	
13	0-255	G(0-255)	
14	0-255	B(0-255)	
15	0-255	INT(0%-100%)	
16	0-255	CCT(2700K-10000K)	
17	0-255	GM(-50-50)	
18	0-255	CCT<-->RGB	
19	0-255	R(0-255)	PIXEL3
20	0-255	G(0-255)	
21	0-255	B(0-255)	
.	0-255	INT(0%-100%)	
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
.	0-255	CCT<-->RGB	
.	0-255	R(0-255)	PIXELn(3<n<11)
.	0-255	G(0-255)	
.	0-255	B(0-255)	
71	0-255	INT(0%-100%)	
72	0-255	CCT(2700K-10000K)	
73	0-255	GM(-50-50)	
74	0-255	CCT<-->RGB	
75	0-255	R(0-255)	PIXEL11
76	0-255	G(0-255)	
77	0-255	B(0-255)	

CCT&HSI 8-bit PIXEL=3			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->HSI	
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL2
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	
10	0-255	CCT<-->HSI	
11	0-255	HUE(0°-360°)	
12	0-255	SAT(0%-100%)	
13	0-255	INT(0%-100%)	PIXEL3
14	0-255	CCT(2700K-10000K)	
15	0-255	GM(-50-50)	
16	0-255	CCT<-->HSI	
17	0-255	HUE(0°-360°)	
18	0-255	SAT(0%-100%)	
.	0-255	INT(0%-100%)	PIXELn(3<n<11)
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
.	0-255	CCT<-->HSI	
.	0-255	HUE(0°-360°)	
.	0-255	SAT(0%-100%)	
61	0-255	INT(0%-100%)	PIXEL11
62	0-255	CCT(2700K-10000K)	
63	0-255	GM(-50-50)	
64	0-255	CCT<-->HSI	
65	0-255	HUE(0°-360°)	
66	0-255	SAT(0%-100%)	

CCT 8-bit PIXEL=3			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	CCT(2700K-10000K)	
6	0-255	GM(-50-50)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	
.	0-255	INT(0%-100%)	PIXELn(3<n<11)
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
31	0-255	INT(0%-100%)	PIXEL11
32	0-255	CCT(2700K-10000K)	
33	0-255	GM(-50-50)	

RGB 8-bit PIXEL=3			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	R(0-255)	
3	0-255	G(0-255)	
4	0-255	B(0-255)	
5	0-255	INT(0%-100%)	PIXEL2
6	0-255	R(0-255)	
7	0-255	G(0-255)	
8	0-255	B(0-255)	
9	0-255	INT(0%-100%)	PIXEL3
10	0-255	R(0-255)	
11	0-255	G(0-255)	
12	0-255	B(0-255)	
.	0-255	INT(0%-100%)	PIXELn(3<n<11)

.	0-255	R(0-255)	PIXEL11
.	0-255	G(0-255)	
.	0-255	B(0-255)	
41	0-255	INT(0%-100%)	
42	0-255	R(0-255)	
43	0-255	G(0-255)	
44	0-255	B(0-255)	

HSI 8-bit PIXEL=3			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	HUE(0°-360°)	
3	0-255	SAT(0%-100%)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	HUE(0°-360°)	
9	0-255	SAT(0%-100%)	
.	0-255	INT(0%-100%)	PIXELn(3<n<11)
.	0-255	HUE(0°-360°)	
.	0-255	SAT(0%-100%)	
31	0-255	INT(0%-100%)	PIXEL11
32	0-255	HUE(0°-360°)	
33	0-255	SAT(0%-100%)	

CCT&RGB 8-bit PIXEL=1			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->RGB	
5	0-255	R(0-255)	

6	0-255	G(0-255)	PIXEL2
7	0-255	B(0-255)	
8	0-255	INT(0%-100%)	
9	0-255	CCT(2700K-10000K)	
10	0-255	GM(-50-50)	
11	0-255	CCT<-->RGB	
12	0-255	R(0-255)	
13	0-255	G(0-255)	
14	0-255	B(0-255)	PIXEL3
15	0-255	INT(0%-100%)	
16	0-255	CCT(2700K-10000K)	
17	0-255	GM(-50-50)	
18	0-255	CCT<-->RGB	
19	0-255	R(0-255)	
20	0-255	G(0-255)	
21	0-255	B(0-255)	
.	0-255	INT(0%-100%)	PIXELn(3<n<33)
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
.	0-255	CCT<-->RGB	
.	0-255	R(0-255)	
.	0-255	G(0-255)	
.	0-255	B(0-255)	
225	0-255	INT(0%-100%)	
226	0-255	CCT(2700K-10000K)	
227	0-255	GM(-50-50)	
228	0-255	CCT<-->RGB	
229	0-255	R(0-255)	
230	0-255	G(0-255)	
231	0-255	B(0-255)	

CCT&HSI 8-bit PIXEL=1

Channel	Value	Function	Description
---------	-------	----------	-------------

1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	CCT<-->HSI	
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL2
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	
10	0-255	CCT<-->HSI	
11	0-255	HUE(0°-360°)	
12	0-255	SAT(0%-100%)	
13	0-255	INT(0%-100%)	PIXEL3
14	0-255	CCT(2700K-10000K)	
15	0-255	GM(-50-50)	
16	0-255	CCT<-->HSI	
17	0-255	HUE(0°-360°)	
18	0-255	SAT(0%-100%)	
.	0-255	INT(0%-100%)	PIXELn(3<n<33)
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
.	0-255	CCT<-->HSI	
.	0-255	HUE(0°-360°)	
.	0-255	SAT(0%-100%)	
193	0-255	INT(0%-100%)	PIXEL33
194	0-255	CCT(2700K-10000K)	
195	0-255	GM(-50-50)	
196	0-255	CCT<-->HSI	
197	0-255	HUE(0°-360°)	
198	0-255	SAT(0%-100%)	

CCT 8-bit PIXEL=1

Channel	Value	Function	Description
---------	-------	----------	-------------

1	0-255	INT(0%-100%)	PIXEL1
2	0-255	CCT(2700K-10000K)	
3	0-255	GM(-50-50)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	CCT(2700K-10000K)	
6	0-255	GM(-50-50)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	CCT(2700K-10000K)	
9	0-255	GM(-50-50)	
.	0-255	INT(0%-100%)	PIXELn(3<n<33)
.	0-255	CCT(2700K-10000K)	
.	0-255	GM(-50-50)	
97	0-255	INT(0%-100%)	PIXEL33
98	0-255	CCT(2700K-10000K)	
99	0-255	GM(-50-50)	

RGB 8-bit PIXEL=1

Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	R(0-255)	
3	0-255	G(0-255)	
4	0-255	B(0-255)	
5	0-255	INT(0%-100%)	PIXEL2
6	0-255	R(0-255)	
7	0-255	G(0-255)	
8	0-255	B(0-255)	
9	0-255	INT(0%-100%)	PIXEL3
10	0-255	R(0-255)	
11	0-255	G(0-255)	
12	0-255	B(0-255)	
.	0-255	INT(0%-100%)	PIXELn(3<n<33)
.	0-255	R(0-255)	
.	0-255	G(0-255)	

.	0-255	B(0-255)	PIXEL33
129	0-255	INT(0%-100%)	
130	0-255	R(0-255)	
131	0-255	G(0-255)	
132	0-255	B(0-255)	

HSI 8-bit PIXEL=1			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	PIXEL1
2	0-255	HUE(0°-360°)	
3	0-255	SAT(0%-100%)	
4	0-255	INT(0%-100%)	PIXEL2
5	0-255	HUE(0°-360°)	
6	0-255	SAT(0%-100%)	
7	0-255	INT(0%-100%)	PIXEL3
8	0-255	HUE(0°-360°)	
9	0-255	SAT(0%-100%)	
.	0-255	INT(0%-100%)	PIXELn(3<n<33)
.	0-255	HUE(0°-360°)	
.	0-255	SAT(0%-100%)	
97	0-255	INT(0%-100%)	PIXEL33
98	0-255	HUE(0°-360°)	
99	0-255	SAT(0%-100%)	

EFFECT 8-bit			
Channel	Value	Function	Description
1	0-255	INT(0%-100%)	Intensity
2	0-9 10-19 20-29	"OFF", "Lightning", "CCT Loop",	EFFECT Type

	30-39 40-49 50-59 60-69 70-79 80-89 90-99 100-109 110-119 120-129 130-255	"Candle", "Bad Bulb", "TV", "Paparazzi", "Explosion", "Pulsing", "Disco", "Cop Car", "Party", "Hue Loop" Reserved	
3	0-127 128-255	Loop Stop	Control
4	0-9 10-19 20-29 30-39 40-49 50-59 60-69 70-79 80-89 90-99 100-255	SPD=1 SPD=2 SPD=3 SPD=4 SPD=5 SPD=6 SPD=7 SPD=8 SPD=9 SPD=10 Reserved	Speed
5	0-255	NA	Valid when type is: "CCT Loop"
	0-255	CCT(2700K-10000K)	Valid when type is: "Lightning", "Candle", "Bad Bulb", "TV", "Paparazzi", "Explosion", "Pulsing"
	0-255	SAT(0%-100%)	Valid when type is: "Disco", "Party", "Hue Loop"

PIXEL FX 8-bit

Channel	Value	Function	Description
---------	-------	----------	-------------

1	0-255	INT(0%-100%)	Intensity
2	0-9 10-19 20-29 30-39 40-49 50-59 60-69	"Rolling", "Rainbow", "BlockGame", "PingPong", "Wave", "Meteor" Reserved	PIXEL FX Type
3	0-127 128-255	ST=0 Stop ST=1 Run	FX Status
4	0-9 10-19 20-29 30-39 40-49 50-59 60-69 70-79 80-89 90-99 100-255	SPD=1 SPD=2 SPD=3 SPD=4 SPD=5 SPD=6 SPD=7 SPD=8 SPD=9 SPD=10 Reserved	Speed
5	0-127 128-255	Dir=0 Left Dir=1 Right	Direction
6-9	See PIXEL FX Parameter Tables in Following Pages		

PIXEL FX: Rolling

Channel	Value	Function	Description
6	0-4 5-9 10-14 15-19 ... 165-169 170-255	COLORS: CCT COLORS: HSI COLORS: 2 COLORS: 3 ... COLORS: 33 Reserved	Color Mode
7	0-4 5-9 10-14 15-19 ... 160-164 165-255	PIXELS=1 PIXELS=2 PIXELS=3 PIXELS=4 ... PIXELS=33 Reserved	Rolling Pixels
8	0-255	CCT(2700K-10000K) HUE(0°-360°)	COLORS=CCT COLORS=HSI

9	0-255	HUE min(0°-360°)	COLORS=2-33
		GM(-50-50)	COLORS=CCT
		SAT(0%-100%)	COLORS=HSI
		HUE max(0°-360°)	COLORS=2-33

PIXEL FX: Rainbow

Channel	Value	Function	Description
6-9		NA	

PIXEL FX: BlockGame

Channel	Value	Function	Description
6	0-255	Forward HUE(0°-360°)	
7	0-255	Forward SAT(0%-100%)	
8	0-255	Background HUE(0°-360°)	
9	0-255	Background SAT(0%-100%)	

PIXEL FX: PingPong

Channel	Value	Function	Description
6	0-255	Forward HUE(0°-360°)	
7	0-255	Forward SAT(0%-100%)	
8	0-255	Background HUE(0°-360°)	
9	0-255	Background SAT(0%-100%)	

PIXEL FX: Wave

Channel	Value	Function	Description
6	0-255	Forward HUE(0°-360°)	
7	0-255	Forward SAT(0%-100%)	
8	0-255	Background HUE(0°-360°)	
9	0-255	Background SAT(0%-100%)	

PIXEL FX: Meteor

Channel	Value	Function	Description
6	0-255	HUE(0°-360°)	
7	0-255	SAT(0%-100%)	

8	0-255	NA	
9	0-255	NA	

GVM

GREAT VIDEO MAKER

Web: www.gvmled.com

B&H Email: bh@gvmled.com

GVM Email: support@gvmled.com

Amazon Email: amazonsupport@gvmled.com

Warehouse Add: 4301 N Delaware ave, unit D. PHILADELPHIA, PA19137, USA